

CEN-AVF-HUB

.AV Framework™ Hub

- > Enables Crestron Fusion® enterprise integration for basic rooms and spaces
- > Extremely cost-effective — supplants the need for a control system and programming
- > Supports up to 15 rooms, each with a single display, switcher, and/or AirMedia® [1]
- > Future support for room occupancy sensors via Cresnet® or infiNET EX® [1]
- > Easy setup and configuration via Web browser user interface
- > Allows scheduling of system turn on and turn off times
- > Compact, stackable “IFE small” form factor
- > Surface or DIN rail mountable using bracket provided
- > Available rack mount and pole mount options [3]
- > PoE network powerable
- > Universal 100-240V external power pack included



The .AV Framework™ Hub enables huddle rooms and other meeting spaces with basic or no AV presentation technology to be integrated as part of a complete **Crestron Fusion®** managed enterprise. A single “AVF Hub” can support up to 15 such rooms, allowing each room’s occupancy [1] and device status to be monitored and managed without the need for any additional control systems or custom programming. Quick setup and configuration is facilitated through an easy-to-use Web browser interface.

Please note, occupancy sensing is not currently supported and will be enabled, along with other features and functions, through future firmware updates.

Enterprise Management Bridge for AV Presentation Systems

In its initial release, the AVF Hub provides a bridge to Crestron Fusion for the Crestron® **HD-MD-400-C-E** HD Scaling Presentation Switcher & Extender 400, the **AM-100** AirMedia® Presentation Gateway [2], and third-party **Crestron Connected®** display devices. Each device simply communicates with the AVF Hub over Ethernet.

Used with the HD-MD-400-C-E, the AVF Hub enables the following functionality:

- Reports the currently selected input source
- Controls display device power via CEC or RS-232 (or Ethernet for Crestron Connected displays) when an input source is connected or disconnected
- Monitors display power status via CEC or Ethernet
- Allows scheduling of system turn on and turn off times via the Web browser interface
- Reports and logs display and source device usage

- Reports various errors to facilitate help desk troubleshooting and enable alert messaging via Crestron Fusion
- Supports up to 15 rooms, each with one HD-MD-400-C-E switcher, one display device, and one optional AM-100 [2]
- Also supports rooms with just a Crestron Connected display and optional AM-100 [2]

Support for additional devices and functions will be enabled in the future.

Integrator Friendly Enclosure

The CEN-AVF-HUB features the Crestron IFE form factor, a compact “Integrator Friendly Enclosure” design that fits almost anywhere and enables a variety of installation options. Its shape allows multiple AVF Hubs and other IFE compliant devices to be stacked together. Using the included mounting bracket, it can be fastened to any flat surface or snapped onto a standard DIN rail. Rack mount and pole mount kits are also available separately.

Power over Ethernet

The CEN-AVF-HUB can be powered through its Ethernet connection using PoE technology. This allows the AVF Hub to be installed in closets and other locations that lack an AC power outlet. To take advantage of this feature, Crestron offers the **PWE-4803RU** PoE Injector [3], which simply connects in line with the Ethernet cable. Crestron also offers Ethernet switches with built-in PoE (models **CEN-SW-POE-5** or **CEN-SWPOE-16** [3]), affording a complete high-performance networking solution capable of powering multiple PoE powered devices.

CEN-AVF-HUB .AV Framework™ Hub



Front View



Rear View

SPECIFICATIONS

Wired Communications

Ethernet: 10/100 Mbps, auto-switching, auto-negotiating, auto-discovery, full/half duplex, industry-standard TCP/IP stack, UDP/IP, CIP, DHCP, SSL, TLS, SSH, SFTP (SSH File Transfer Protocol), FIPS 140-2 compliant encryption, IEEE 802.1X, IPv4 or IPv6, Active Directory authentication, IIS v.6.0 Web Server, SMTP e-mail client, IEEE 802.3at Type 1 compliant
Cresnet®: Cresnet master mode^[1]

Wireless Communications^[1]

RF Transceiver: infiNET EX® 2-way RF, 2.4 GHz ISM Channels 11-26 (2400 to 2483.5 MHz), default channel 15; IEEE 802.15.4 compliant
Transmit Power: +20 dBm (US/NA model CEN-AVF-HUB);
+8 dBm (International model CENI-AVF-HUB)

Range (typical): 150 ft (46 m) indoor, 250 ft (76 m) outdoor to nearest mesh network device(s); subject to site-specific conditions and individual device capabilities^[4]

Connectors

MEMORY: (1) Micro SD memory card slot;
Accepts one Micro SD card for storage of log files

COMPUTER: (1) USB Type Micro-B female;
Service port for factory use only

NET: (1) 4-pin 3.5 mm detachable terminal block, Cresnet master port^[1];
Outputs power to Cresnet devices if a power pack is connected to the 24 VDC power input jack;
Alternately functions as a Cresnet power input to power the unit from a Cresnet power supply^[3];
See "Power Requirements" for additional specifications

24 VDC 0.75A: (1) 2.1 x 5.5 mm DC power connector;
24 Volt DC power input;
PW-2407WU power pack included;
Passes through to NET port to power Cresnet devices;
See "Power Requirements" for additional specifications

G: (1) 4-40 screw, chassis ground lug

LAN PoE: (1) 8-pin RJ45 female;
10Base-T/100Base-TX Ethernet port, Power over Ethernet compliant

Controls & Indicators

PWR: (1) Green LED, indicates operating power is supplied via the power pack, PoE, or Cresnet

NET: (1) Amber LED, indicates communication with Cresnet devices
PAIR: (1) Red LED, indicates when pairing with an infiNET EX wireless device

HW-R: (1) Recessed pushbutton for hardware reset

SW-R: (1) Recessed pushbutton for software reset

LAN PoE (rear): (1) Green and (1) amber LEDs, green indicates Ethernet link status, amber indicates Ethernet activity

Power Requirements

Power Source Options: Power pack (included), PoE, or Cresnet; safe to connect multiple power sources

Power Pack: 100-240 Volts AC, 50/60 Hz input; 0.75 Amps @ 24 Volts DC output; model PW-2407WU included

Power over Ethernet: IEEE 802.3at Type 1 (802.3af compatible) Class 0 (12.95 W) PoE Powered Device

Cresnet Power Usage: 4 Watts (0.17 Amp @ 24 Volts DC)

Available Cresnet Power: 14 Watts (1 Amp @ 24 Volts DC) when powered by the PW-2407WU power pack (included)

Power Consumption: 4 Watts (not including any connected Cresnet devices)

Environmental

Temperature: 41° to 113° F (5° to 45° C)

Humidity: 10% to 90% RH (non-condensing)

Heat Dissipation: 14 BTU/Hr

Construction

Enclosure: IFE small form factor, black and blue plastic

Mounting: Freestanding, stackable, surface mount, or 35 mm DIN EN 60715 rail mount; Occupies 8 DIN module spaces (144 mm); Surface/DIN rail mounting bracket included, optional rack mount and pole mount kits sold separately

Dimensions

Height: 1.35 in (35 mm), 1.77 in (45 mm) with bracket

Width: 5.04 in (129 mm), 5.36 in (137 mm) with bracket

Depth: 5.04 in (129 mm)

CEN-AVF-HUB .AV Framework™ Hub



Shown with mounting bracket

Weight

9.9 oz (281 g);
11.3 oz (321 g) with bracket

MODELS & ACCESSORIES

Available Models

CEN-AVF-HUB: .AV Framework™ Hub
CENI-AVF-HUB: .AV Framework™ Hub – International Version

Included Accessories

PW-2407WU: 24 Volt DC Power Pack

Available Accessories

RMK-IFE-1U: IFE Rack Mount Kit
PLMK-IFE-101: IFE Pole Mount Kit
CLW-EXPEX: infiNET EX® Wireless Expander
GLA-EXPEX: Crestron Green Light® Wireless Expander for infiNET EX® Networks
PWE-4803RU: PoE Injector
CEN-SW-POE-5: 5-Port PoE Switch
CEN-SWPOE-16: 16-Port Managed PoE Switch

Notes:

1. Occupancy sensing, Cresnet communication, and infiNET EX wireless communication are not currently supported and will be enabled via future firmware updates. When that functionality is enabled, the Cresnet port and infiNET EX transceiver will be strictly for use with specific Crestron occupancy sensors and other specific devices. The CEN-AVF-HUB will not function as a general purpose infiNET EX gateway or Ethernet-to-Cresnet bridge.
2. Use with the AM-100 AirMedia Presentation Gateway requires use of the AirMedia Windows® or OS X® Deployable Application, or the forthcoming [Crestron PinPoint™ App](#).
3. Item(s) sold separately.
4. The total range of an infiNET EX wireless network is dependent on the placement and capabilities of each network device. A mesh network topology is employed so every "EX" device on the network acts as an "expander," relaying wireless commands between the gateway and all the other EX devices on the network. Each infiNET EX device that is added to the network effectively increases the range and stability of the entire network by providing multiple redundant signal paths. The wireless range between any two EX devices is typically up to 150 ft (46 m) indoors. Battery-powered infiNET EX devices do not provide expander functionality, and may have a reduced wireless range. Consult the specifications for each network device to confirm its actual wireless capabilities. Crestron also offers dedicated infiNET EX expanders (models [CLW-EXPEX](#) or [GLA-EXPEX](#), sold separately), which may be deployed to fill gaps in coverage and extend the wireless range of the mesh network. A maximum of five infiNET EX expanders may be deployed on an infiNET EX network.

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/salesreps or by calling 800-237-2041.

The specific patents that cover Crestron products are listed online at: patents.crestron.com.

Certain Crestron products contain open source software. For specific information, please visit www.crestron.com/opensource.

Crestron, the Crestron Logo, .AV Framework, AirMedia, Cresnet, Crestron Connected, Crestron Fusion, infiNET EX, and PinPoint are either trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and/or other countries. OS X is either a trademark or registered trademark of Apple Inc. in the United States and/or other countries. Windows is either a trademark or registered trademark of Microsoft Corporation in the United States and/or other countries. Other trademarks, registered trademarks, and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. Crestron is not responsible for errors in typography or photography. Specifications are subject to change without notice. ©2016 Crestron Electronics, Inc.

