

HQUltra730A

HQUltra 4K Events AV Scaler-Switcher & LED Scaler with HQUltraFast Input Switching, Line Level & Microphone Inputs, Power Amp



HQUltra730A is a universal live events scaler-switcher & LED videowall image scaler based on Calibre's proprietary class-leading HQUltra 4K image processing technology.

Calibre's HQUltra 4K scaling provides best in class picture quality with low latency video processing.

Multi-region high-bit-depth soft edge blend with black level correction for seamless soft-edge blending.

Featuring Calibre's proprietary HQUltraFast input channel switching able to switch input channels in under a quarter of a second, HQUltra730A has a wide range of input connectivity for today's digitally connected ProAV world, but still is able to support legacy formats too, all with great image quality.

HQView730A includes stereo analogue audio inputs and outputs with audio-follow-video capability. There are two microphone inputs with phantom power available and internal mixer for talk-over. The internal power amplifier provides 2x15W RMS to directly drive loudspeakers in meeting rooms and smaller conference room, plus line level balanced stereo outputs to drive an external amplifier or powered loudspeakers,

HQUltra730A includes front panel controls with easy to read front panel menu system as well as remote control via inbuilt webserver or easy to implement protocol.

For in-camera use a Genlock input is provided compatible with bi or tri-level sync or black & burst.

For LED videowalls HQUltra730A has a special LED mode with per-edge pixel-accurate image sizing for fast pixel-perfect image alignment on LED videowalls.

- Perfect scaling with Calibre's HQUltra low-latency 4K best-in-class proprietary scaling algorithms
- HQUltraFast proprietary typical 0.25 seconds input channel switching technology
- LED Videowall Mode with per-edge pixel-accurate custom sizing
- Soft-edge blend with high bit depth processing & black level correction
- Front panel jog-wheel and LCD display for fast easy set-up in the field. Remote control via webserver or simple API
- 10 Video Inputs: 2xHDMI 4K, 1xHDMI HD, 1xDisplayPort 4K, 2x3G-SDI, 1xVGA, 1xCVBS, 1xDVI-U (DVI/HDMI & VGA/RGBS/YPbPr)
- 3 Video Outputs: 1xHDMI 4K, 1xDVI/HDMI, 1x3G-SDI
- 7x Line Level Stereo Audio Inputs
- 2x Microphone Inputs with Phantom Power and Audio Mixer
- Stereo Audio Power Amplifier with 2x15W RMS Loudspeaker Outputs
- Stereo Balanced Line Level Audio Outputs
- Picture in Picture
- Brightness, Contrast, Saturation controls for all source types. RGB calibration controls (not 4:2:0 in to 4:2:0 out)
- Flexible Aspect Ratio Conversion
- Full Genlock and Source Lock for in-camera & broadcast applications
- Audio de-embed from HDMI, DisplayPort and 3G-SDI inputs to S/PDIF, re-embed to HDMI outputs
- Optional H.264 HD Streaming Video Input



Calibre UK Ltd,
Cornwall House, Cornwall Terrace,
Bradford,
West Yorkshire
BD8 7JS. UK

proavsales@calibreuk.com
+44 1274 940770
+1 438 448 3614
+86 95013 5890 6926
www.calibreuk.com

HQUltra730A

HQUltra 4K Events AV Scaler-Switcher & LED Scaler with HQUltraFast Input Switching, Line Level & Microphone Inputs, Power Amp

Inputs

2x HDMI 4K, 1x HDMI HD, 1x DisplayPort 4K, 2x 3G-SDI
 1x DVI-U supporting VESA modes, SD, HD, can be configured as fourth HDMI input.
 DVI-U input also simultaneously supports VGA/RGbs/YPbPr legacy analog formats with suitable cable.
 1x VGA Analog, 1x Composite PAL/NTSC/SECAM
 1x Genlock reference sync i/p, supports bi/tri-level or black&burst 50/59.94/60Hz sync
 Optional H.264 Streaming Video Input via Gigabit Ethernet Port

HDCP supported on all HDMI/DVI/DisplayPort I/O

6x Line Level Stereo Audio via 3.5mm Jack
 1x Line Level Stereo Audio via 2xRCA
 2x Microphone Input with 48V Phantom Power via 6.35mm Jack

Supported digital input and output formats:

4K/UHD (HDMI 4K/DisplayPort /HDBaseT only)
 3840x2160p, 4096x2160p 23.97/24/25/29.94/30/50/59.94/60;
 UHD/4K 50/59.94/60p modes supported in 4:2:0 format.
 HD 1280x720p, 1920x1080i, 1920x1080psf,
 1920x1080p23.97/24/25/29.94/30/50/59.94/60,
 2048x1080p23.97/24/25/29.94/30/50/59.94/60.
 ED 480p, 576p (not via SDI), SD 625i (576i), 525i (480i)
 Common VESA graphics formats from VGA to 4K,
 (Modes higher than WUXGA on 4K capable input channels only)

Outputs

1x HDMI 4K via HDMI connector
 1x DVI/HDMI via DVI connector
 1x 3G-SDI
 1x S/PDIF digital audio via RCA

NB: 3G-SDI output is disabled with HDCP-encrypted input and also for incompatible output modes.
 All outputs are otherwise available simultaneously, with the same image shown on each.

1x Loudspeaker Connector, 2x15W RMS
 1x Line Level Balanced Stereo

Supported Switching & Sync Modes

HQUltraFast input Switching in Genlock and Free-Run modes
 Also supports Source Lock when HQUltraFast not required

User Controls

Front panel jog-wheel and LCD menu display for fast set-up.
 Keypad for direct input selection and integral indicator LEDs.
 Remote control via RS232, TCP/IP API and Web Server.
 Gigabit Ethernet for webserver and remote control API

Power Requirements

100-264VAC, 65W typical

Warranty

3-years return to base warranty covers parts and labour.

Order Codes

HQView730A with Audio – Order Code **H730A**
 HQView730ASV with Audio & Streaming Video Input – Order Code **H730ASV**



HQView model >	H210	H310	H320	H325	L530	H620	H625	H630	H670	H730	H770	L720	L725	L730	L770
Front LCD menu or OSD control	OSD	OSD	OSD	OSD	LCD	LCD	LCD	LCD	LCD	LCD	LCD	LCD	LCD	LCD	LCD
HDMI 4K Inputs						■(2)	■(2)	■(2)	■(2)	■(2)	■(2)	■(2)	■(2)	■(2)	■(2)
HDMI HD Input				■	■	■	■	■	■	■	■	■	■	■	■
DVI/HDMI HD Input		■	■	■	■	■	■	■	■	■	■	■	■	■	■
HDBaseT 4K Input						■	■	■	■	■	■	■	■	■	■
DisplayPort 4K Input						■	■	■	■	■	■	■	■	■	■
Component Input		BNCs	BNCs		BNCs	DVI-U	DVI-U	DVI-U	DVI-U	DVI-U	DVI-U	DVI-U	DVI-U	DVI-U	DVI-U
Composite Input(s)				■(2)											
VGA Analog Input		DVI-I	DVI-I												
3G-SDI Input(s)	■							■(2)	■(2)	■(2)	■(2)			■(2)	■(2)
DVI / HDMI HD Output	■	■	■	■	■	■	■	■	■	■	■	■	■	■	■
HDMI 4K Output						■	■	■	■	■	■	■	■	■	■
HDBaseT 4K Output						■	■	■	■	■	■	■	■	■	■
VGA Analog Output															
3G-SDI Output						■	■	■	■	■	■	■	■	■	■
3G-SDI Audio embed/de-embed & SPDIF						■	■	■	■	■	■	■	■	■	■
HQV Processing	■	■	■	■	■	■	■	■	■	■	■	■	■	■	■
HQUltra 4K Low-Latency Processing						■	■	■	■	■	■	■	■	■	■
HQUltraFast High Speed Input Switching						■	■	■	■	■	■	■	■	■	■
PIP						■	■	■	■	■	■	■	■	■	■
TCP/IP Webserver & API Control	■	■	■	■	■	■	■	■	■	■	■	■	■	■	■
Geometry Correction, 4-Corner, Rotate	■	■	■	■	■	■	■	■	■	■	■	■	■	■	■
Mesh-based Warp, config via PC App				■	■										
Genlock - V-Lock						■	■	■	■	■	■	■	■	■	■
Genlock – H&V or Crosslock								■	■	■	■			■	■
Pan, Zoom, Tilt	■	■	■	■	■	■	■	■	■	■	■	■	■	■	■
Edge Blending						■	■	■	■	■	■	■	■	■	■
Edge Blend Black Level Correction						■	■	■	■	■	■	■	■	■	■
Videowall mode with auto PTZ		■	■	■	■	■	■	■	■	■	■	■	■	■	■
LED Videowall Per-Edge Sizing						■	■	■	■	■	■	■	■	■	■
Analogue Audio In, Out and Power Amp										Opt	Opt				
<i>Opt: option fitted to models with "A" suffix</i>															
Streaming Video Input via Network Port										Opt	Opt	Opt	Opt	Opt	Opt
<i>Opt: option fitted to models with "SV" suffix</i>															

Calibre UK Ltd,
Cornwall House, Cornwall Terrace,
Bradford,
West Yorkshire
BD8 7JS. UK

proavsales@calibreuk.com
+44 1274 940770
+1 438 448 3614
+86 95013 5890 6926
www.calibreuk.com